



Technical Bulletin

Bulletin Number: 144

Date: 7/9/2004

Released By: dhs

Classification

Product Family: LP-X CONTROLLER

Subject: Slow response of the Page Select switch

Initial releases of the LP-X24 controller have slow response on the Page Select rotary encoder. If the page knob is turned too quickly, the board does not respond to the page change encoder.

There is a simple remedy for this. A single capacitor change will improve the performance of the page switch.

This update is available from Leprecon, or can be implemented by a qualified technician. If you are looking to do it yourself, here is the information that you need.

On fader board #30-7004, replace capacitor C501 with a disc capacitor with a value of 470 pf. This part is available from Leprecon as Part Number 02-0014.