

# CONTROLLERS



SOFTPATCH



CUE STACK WITH GO BUTTON

**Leprecon**<sup>®</sup>  
Lighting for Professionals



*The compact and economical 600 Series Memory Consoles are fully featured and designed to withstand the most demanding conditions*


Features:

Two Scene Preset Mode 

Softpatch 

Chase Memory 

Bump Buttons with Add and Solo Modes 

Cue Stack and "Go" Button 



[www.leprecon.com](http://www.leprecon.com)

Made in the USA

Leprecon's twelve channel LP-612 or twenty-four channel LP-624 consoles incorporate the same full travel faders and rugged aluminum chassis design that make our touring consoles the most reliable in the industry. With full size fader knobs, quick action-bump buttons, and big bright LED's, these consoles were designed and built for professional use.

The console includes: two scene preset mode with twelve or twenty-four channels; switchable Add or Solo momentary buttons for each channel; and dipless crossfade between manual scenes. Presets may be "piled on" in any combination, and are assigned to one of four memory pages. Preview mode allows cues to be checked without bringing up the scene on stage. An existing cue may be easily edited using the manual scene faders without re-recording the entire cue.



Cue Stack offers 50 programmable cues with crossfader and "GO" button control. Fade times may be assigned to each scene. A two-character display is used to indicate current or new cue and programmed fade times assigned to each scene. Four programmed and seven programmable patterns of up to 20 steps are provided. Programmable patterns are recorded, previewed, and edited as easily as the preset cues. The rate of each pattern may be saved with the chase, eliminating the need to adjust the rate pot when chase is recalled. Control outputs include 3-pin microplex and 5-pin DMX-512 standard. Analog 0-10V via Cinch Jones optional. All protocols can be used simultaneously.

### 600 Series Memory Consoles

#### LP-612

#### LP-624

Channel	12	24
Two Scene — Preset	Yes	Yes
Softpatch	Yes	Yes
Preset Faders	12	24
Preset Memories	48	96
Cue Stack	Yes	Yes
Go Button	Yes	Yes
Bump Buttons	Yes	Yes
Dipless Crossfader	Yes	Yes
Chase Memory	11 Patterns-24 Steps Real Level Memories	11 Patterns-24 Steps Real Level Memories
Microplex Output	3-pin Microphone cable	3-pin Microphone cable
DMX Output	5-pin XLR	5-pin XLR
Times Fades	Yes	Yes
Blind Edit	Yes	Yes
120V External power supply	12-15 VAC, 1 Amp	12-15 VAC, 1 Amp
Weight — lbs (packaged)	9	13
Height, Width, Depth (inches)	2.87 x 15.41 x 10.13	2.87 x 25.375 x 10.13
<b>Options</b>		
Analog Output	(2 each) 8-pin CJ Male	(1 each) 27-pin CJ Male
Dust Cover	Gray vinyl with Lepecon logo	Gray vinyl with Lepecon logo

#### FULL TWO YEAR WARRANTY

For a period of two years from the date of sale, Leprecon, LLC, will replace any defective parts and will repair any defective module returned to the factory prepaid, without charge for parts or labor. Please consult your dealer for full warranty details.

**Leprecon** [www.leprecon.com](http://www.leprecon.com)

Leprecon, LLC, P.O. Box 218, 10087 Industrial Drive, Hamburg MI 48139-0218, Phone 888-422-3537, Fax 810-231-1631, sales@leprecon.com

Copyright 28-0037C